

# Maintenance and updates

Under the menu item **Services > Maintenance**, the access procedure to the update server is set in order to be able to carry out remote maintenance or install updates for TightGate-Pro.

## Note

The relevant settings apply to all nodes in computer networks (cluster systems), with the exception of the menu option **Redirected remote port**. This setting is made individually for each node so that individual nodes can be accessed at the same time via remote maintenance.

These setting options are available:

Menu item	Description	Recommended value
Connection method(*)	<p>Selection of the connection method for how TightGate-Pro can obtain updates from the update servers of m-privacy GmbH . Depending on availability in the network, the appropriate connection method can be selected:</p> <p><b>SSH-443</b> If TightGate-Pro has unrestricted access to the Internet on port 443 and is also authorised to use the SSH protocol via the port, this value should be used.</p> <p><b>SSH out</b> If TightGate-Pro can establish outgoing SSH connections via port 22, this value should be used. The update connection can be restricted here at the firewall to the IP address 85.214.123.128.</p> <p><b>HTTP Proxy SSL</b> <b>HTTP Proxy Connect</b> If TightGate-Pro accesses the Internet via a proxy, one of the proxy methods should be used.</p> <p><b>Note:</b> The connection method <b>SSH out</b> should only be used if the other methods do not work, as these methods do not distribute the load across the various update servers of m-privacy GmbH .</p>	<b>SSH-443</b> or <b>HTTP proxy</b> , alternatively <b>SSH outgoing</b>
Administration by m-privacy(*)	Specifies that the maintenance IPs of m-privacy are included in the list of authorised IPs for <b>Admin Networks</b> .	
Redirected remote port	Port via which the technical customer service of m-privacy GmbH connects to your TightGate-Pro. The remote maintenance port is only activated if the administrator <b>maint</b> explicitly opens the remote maintenance access.	Consult the m-privacy GmbH .

After configuration, the settings must be saved and applied via the menu options **Save** and **Apply**.

From:  
<https://help.m-privacy.de/> -

Permanent link:  
<https://help.m-privacy.de/doku.php/en:tightgate-pro:konfiguration:dienste:wartungszugang>

Last update: **2025/09/23 13:29**

